

Generator Information

Model NG400

Engine driven generator set.

Rated: 350kW / 438kVA Continuous at 277/480 Volt, Three Phase, 60 Hz

Engine/Generator:

- PSI HD 21.9L ENGINE: EPA Certified Prime / Mobile Use
- 50 C Ambient Radiator
- Electronic Isochronous Governor
- Automatic Dual Fuel Kit: NG/LP
- Equipped w/ LP Vaporizer Kit
- MARATHON ALTERNATOR: (Oversized)
- Brushless rotating field generator with class H insulation
- DISTRIBUTION CONNECTIONS:
- 600 Amp Frame Main Line Circuit Breaker
- Electronic Motor Operated MLCB w/ Shunt Trips & Aux Contacts

DISTRIBUTION CONNECTIONS:

- 600 Amp Frame Main Line Circuit Breaker
- Electronic Motor Operated MLCB w/ Shunt Trips & Aux Contacts

GENERATOR ISOLATION & MAINTENANCE PANEL

- Provides No-Shutdown PM Capability & or Seamless Paralleling
- 1200 Amp Buss
- 2-600 Amp Generator Disconnect Breakers
- (3) 20 Amp - 120VAC Duplex Receptacles
- NFPA-110 Compliant
- Enhanced Gen Protection & Auto Synchronizer for Paralleling
- Remote 2-wire Start/Stop Control
- Able to Parallel up to 32 units in Sequence
- Extended Runtime Features: 1,000 HR Service Interval

Features

- 17 Gallon Oil Day Tank w/ Sight Glass
- Heavy Duty Oilfield Skid
- Solid Seal Welded Floor w/ 150%+ Fluid Containment
- Multiple Containment Drains w/ Plugs
- Sound Attenuated Weatherproof Enclosure
- Noise Reducing Fire Retardant Fiberglass Insulation w/ Galv. Perf Liner
- Gas Leak Detection System - Wired to Controller
- Emergency Stop Switch
- 2-STAGE FUEL SCRUBBER § Equipped w/ Auto Dump & Safety Shutdowns Wired to Controller
- Fisher CS800 & 621 Fuel Step Down Pressure Regulators